



FEASA™ LED ANALYSER

The Innovative Solution for Testing LEDs

The Feasa Analyser is an innovative solution for testing multiple LEDs simultaneously for Color and Brightness. There are two Models – Feasa I(ICT) and Feasa F(Functional). These can be ordered in 3, 5, 10 and 20 Channel configurations.

When choosing which Model is most suitable for your application there are a number of issues to consider. In this regard the choice of Interface is very important.

INTERFACES

	<u>Feasa I</u>	<u>Feasa F</u>
USB	NO	YES
RS232	YES	YES
10/20 Pin Port - Frequency Out	YES	NO
10/20 Pin Port - Synchronous Serial	YES	NO
Daisy Chain	NO	YES

USB offers a very simple interface to the LED Analyser with no requirement for an additional power supply. Very high baud rates, up to 460800 baud, are available.

The **RS232 Serial Port** is easy to use with a max baud rate of 115200. It requires the use of an external power supply.

The **20pin ICT Port** can be used in either Frequency Out or Synchronous Serial Mode.

Frequency Out

The Frequency Out protocol can be used where access to an RS232 Serial Port is not available. Three frequencies are used to represent the Color and Intensity of the LEDs.

Synchronous Serial Port

The Synchronous Serial protocol is suitable when tester resources are limited or no other options are available.

Daisy Chain

Multiple LED Analysers can be connected together using the Daisy Chain Connectors. Only one RS232 Serial Port or USB Port is required to connect up to 30 LED Analysers.



Feasa Enterprises Ltd.
Castletroy • Limerick • Ireland

Telephone: + 353 61 330333 - Fax : + 353 61 330452 - Website: www.feasa.ie

Registered Office: Feasa Enterprises Limited, Holland Road, National Technology Park, Castletroy, Co.Limerick, Ireland.
Registered in Ireland, No. 106933. Copyright © 2011 Feasa Enterprises Limited. All rights reserved.



FEASA™ LED ANALYSER

The Innovative Solution for Testing LEDs

TEST TIME

The speed of the test is dependent on the intensity of the LEDs being tested, i.e. Bright LEDs have a shorter Test Time, Dimmer LEDs have a longer Test Time.

The capture (measurement) of up to 20 LEDs is done in parallel and can be achieved in times as fast as 1.2ms depending on the Intensity (Brightness).

The data is read back from each fiber sequentially and takes approximately 5ms per fiber, for example:

Ultra High Bright LEDs

- 1 LED - Capture Time is 2ms and Read Back is 5ms, Total 7ms
- 20 LEDs - Capture Time is 2ms and Read Back is 100ms, Total 102ms

Dim LEDs

- 1 LED - Capture Time is 650ms and Read Back is 5ms, Total 655ms
- 20 LEDs - Capture Time is 650ms and Read Back is 100ms, Total 750ms

USB / RS232 SERIAL PORT – TEST CAPTURE TIMES

Range	Capture Time
C (Auto Capture)	350ms
C1 (Low Intensity)	650ms
C2 (Medium Intensity)	200ms
C3 (High Intensity)	22ms
C4 (Super High Intensity)	4ms
C5 (Ultra High Intensity)	2ms

The Read Back Time per fiber is always approximately 5ms.

For ICT the Capture Times are the same as USB/RS232 Serial Port. However, the Read Back Times are dependent on the frequencies being measured. Using an Agilent i3070 the Read Back Times are 400ms to 700ms approximately.



Feasa Enterprises Ltd.
Castletroy • Limerick • Ireland

Telephone: + 353 61 330333 - Fax : + 353 61 330452 - Website: www.feasa.ie

Registered Office: Feasa Enterprises Limited, Holland Road, National Technology Park, Castletroy, Co.Limerick, Ireland.
Registered in Ireland, No. 106933. Copyright © 2011 Feasa Enterprises Limited. All rights reserved.



FEASA™ LED ANALYSER

The Innovative Solution for Testing LEDs

OUTPUTS

<u>USB / RS232</u>	- Red, Green, Blue (RGB) - Hue, Saturation, Intensity (HSI) - Dominant Wavelength - CCT - CIE xy - CIE u'v'
<u>Frequency Out</u>	- Hue, Saturation, Intensity (HSI)
<u>Synchronous Serial</u>	- Red, Green, Blue (RGB) - Hue, Saturation, Intensity (HSI) - CCT - CIE xy

DRIVERS/SOFTWARE

Feasa provides a comprehensive suite of Drivers and Software for ease of use.

	<u>Feasa I</u>	<u>Feasa F</u>
Test Models for Agilent i3070	YES	NO
Test Code for Teradyne	YES	NO
DLL used for Testing	YES	YES
Programming examples in Labview, C++	YES	YES

In addition, Feasa also provides a number of programmes to allow for the most efficient and appropriate use of the analyser.

APPLICATIONS

Indicator LEDs

- RJ45 Connectors
- Display Panels
- Emergency Signals
- Traffic Lights
- Railway Signals

Automotive

- Daytime Running Lights
- Brake Lights
- Centre High Mount Stop Lights
- Side Turn Signals
- Emergency Stop Signal

Interior Lights (Automotive & Avionics)

- Dashboard
- Map Lights
- Mood Lights

LCD Backlighting

- TV
- Notebook/PC
- Cell Phones/Smart Phones

Aviation Lighting

- Landing Lights



Feasa Enterprises Ltd.

Castletroy • Limerick • Ireland

Telephone: + 353 61 330333 - Fax : + 353 61 330452 - Website: www.feasa.ie

Registered Office: Feasa Enterprises Limited, Holland Road, National Technology Park, Castletroy, Co.Limerick, Ireland.
Registered in Ireland, No. 106933. Copyright © 2011 Feasa Enterprises Limited. All rights reserved.



FEASA™ LED ANALYSER

The Innovative Solution for Testing LEDs

SPECIFICATIONS

	<u>Feasa I</u>	<u>Feasa F</u>
OPTICAL		
Total Operating Wavelength Range	450nm to 650nm	450nm to 650nm
ACCURACY		
Dominant Wavelength	± 5nm @ 550nm	± 5nm @ 550nm
Correlated Color Temperature	± 200K @ 2856K	± 200K @ 2856K
Chromaticity – Typical	± 0.01 @ x=0.33, y=0.33	± 0.01 @ x=0.33, y=0.33
REPEATABILITY		
Dominant Wavelength	± 1nm	± 1nm
Correlated Color Temperature	± 50K @ 2856K	± 50K @ 2856K
Chromaticity xy	± 0.0015	± 0.0015
Hue	< 1	< 1
Saturation	< 1%	< 1%
Intensity	< 1%	< 1%
ELECTRICAL		
Supply Voltage	5.0V	5.0V
Supply Current	180mA	180mA
PHYSICAL		
Dimensions of 3, 5, 10 Channel	100mm x 29mm x 50mm	86mm x 57mm x 55mm
Dimensions of 20 Channel	140mm x 29mm x 50mm	127mm x 57mm x 55mm
Fiber Length	0.6m	0.6m
Fiber Diameter	1.0mm, incl. cladding	1.0mm, incl. cladding
Minimum Bend Radius of Fiber	15mm	15mm
Operating Temperature Range	0°C to +50°C	0°C to +50°C

ORDERING INFORMATION

<u>Feasa LED Analyser</u>	<u>Feasa I</u>	<u>Feasa F</u>
3 Channel	Part No.: Feasa 3I	Part No.: Feasa 3F
5 Channel	Part No.: Feasa 5I	Part No.: Feasa 5F
10 Channel	Part No.: Feasa 10I	Part No.: Feasa 10F
20 Channel	Part No.: Feasa 20I	Part No.: Feasa 20F



Feasa Enterprises Ltd.
Castletroy • Limerick • Ireland

Telephone: + 353 61 330333 - Fax: + 353 61 330452 - Website: www.feasa.ie

Registered Office: Feasa Enterprises Limited, Holland Road, National Technology Park, Castletroy, Co.Limerick, Ireland.
Registered in Ireland, No. 106933. Copyright © 2011 Feasa Enterprises Limited. All rights reserved.